



# SPECIFICATIONS

PDICS6

PDICS82



PDICS54  
PDICS64  
PDICS8



WWW.PYLEUSA.COM

## MANUFACTURER'S LIMITED ONE YEAR WARRANTY

**PYLE USA** warrants this unit to be free from defective material or workmanship and will repair or replace this unit or any part there of if it proves defective in normal use or service within one (1) years from the date of original purchase.

Our obligation under this warranty is limited to the repairing or replacing at our discretion, the defective instrument or any part there of when it is returned, transportation prepaid to the Pyle Service Center at the address below. This warranty will be considered void if the unit has been tampered with, improperly serviced, subjected to abuse or misuse or if installed in a commercial vehicle. This warranty does not cover accidental damage. When returning this unit for service, please include \$15.00 for return postage and handling.

Send your unit to:

**PYLE SERVICE CENTER**  
1600-63rd Street  
Brooklyn, New York 11204 USA

**IMPORTANT:** Pack carefully in original carton if possible. We are not responsible for damage incurred in returning items for repair. A letter stating your exact street address, daytime phone number and the problem you are experiencing should be included. You must also enclose a copy of the original receipt as proof of date of purchase.

## About Pyle Series CEILING SPEAKER

Congratulations ! You have purchased one of our high quality Pyle SPEAKER. After the numerous testing and investigate by our professional engineers, Pyle Series SPEAKER not only is in unique design, but also could deliver consistent and high performance.

The General Features of Pyle Series SPEAKER Include :

PDICS6 :

6.5" WOOFER  
0.76" HIGH TEMPERATURE VOICE COIL  
1.5" TWEETER CUP  
120 WATTS PEAK POWER  
FREQUENCY RESPONSE : 80-16K HZ  
8 OHM IMPEDANCE

PDICS8 :

8" WOOFER  
1" HIGH TEMPERATURE VOICE COIL  
1.5" TWEETER CUP  
150 WATTS PEAK POWER  
FREQUENCY RESPONSE : 60-16K HZ  
8 OHM IMPEDANCE  
100V TRANSFORMER TAPPING AT :  
8 OHM, 10W

PDICS8 :

8" WOOFER  
1.0" HIGH TEMPERATURE VOICE COIL  
1.5" TWEETER CUP  
200 WATTS PEAK POWER  
FREQUENCY RESPONSE : 60-16K HZ  
SPL : 89DB  
8 OHM IMPEDANCE

PDICS64 :


6.5" WOOFER  
0.76" HIGH TEMPERATURE VOICE COIL  
1.0" TWEETER CUP  
150 WATTS PEAK POWER  
FREQUENCY RESPONSE : 70-16K HZ  
SPL : 89DB  
8 OHM IMPEDANCE  
100V TRANSFORMER  
8 OHM, 5W

PDICS54 :


5" WOOFER  
0.76" HIGH TEMPERATURE VOICE COIL  
1.2" TWEETER CUP  
100 WATTS PEAK POWER  
FREQUENCY RESPONSE : 90-16K HZ  
SPL : 89DB  
8 OHM IMPEDANCE  
100V TRANSFORMER  
8 OHM, 5W

We do confident that Pyle Series SPEAKER will bring you many hours of enjoyment over the years .

PDICS6




PDICS82




MODEL NO.	PDICS6	PDICS82
WOOFER	1x6.5"	1x8"
IMPEDANCE	8 OHM	8 OHM
VOICE COIL	0.76"	1"
RESPONSE	80-16K HZ	60-16K HZ
SPL(DB)	88	89
TRANSFORMER	WITHOUT	WITHOUT
PEAK POWER	120 WATTS	150 WATTS


PDICS54



PDICS64



PDICS8



MODEL NO.	PDICS54	PDICS64	PDICS8
WOOFER	1x5"	1x6.5"	1x8"
IMPEDANCE	8 OHM	8 OHM	8 OHM
VOICE COIL	0.76"	0.76"	1.0"
RESPONSE	90-16K HZ	70-16K HZ	60-16K HZ
SPL(DB)	89	89	89
TRANSFORMER	100V 5W	100V 5W	100V 5W
PEAK POWER	100 WATTS	150 WATTS	200 WATTS

PYLE continually strives to improve the performance and value of its products. All specifications are subject to change.